

Number	Page	Register Name	Size	Address	Setting value
1	0	Page Select Register	8	0x00	0x00
2	0	Software Reset Register	8	0x01	0x01
3	0	Page Select Register	8	0x00	0x01
4	1	LDO Control Register	8	0x02	0x04
5	1	Page Select Register	8	0x00	0x00
6	0	Clock Setting Register 1 Multiplexers	8	0x04	0x03
7	0	Clock Setting Register 2 PLL P and R Values	8	0x05	0x94
8	0	Clock Setting Register 3 PLL J Values	8	0x06	0x07
9	0	Clock Setting Register 4 PLL D Values (MSB)	8	0x07	0x00
10	0	Clock Setting Register 5 PLL D Values (LSB)	8	0x08	0x00
Add delay of 15 ms					
11	0	Clock Setting Register 6 NDAC Values	8	0x0B	0x82
12	0	Clock Setting Register 7 MDAC Values	8	0x0C	0x87
13	0	DAC OSR Setting Register 1 MSB Values	8	0x0D	0x00
14	0	DAC OSR Setting Register 2 LSB Values	8	0x0E	0x80
15	0	Clock Setting Register 10 Multiplexers	8	0x19	0x00
16	0	Clock Setting Register 11 CLKOUT M divider value	8	0x1A	0x01
17	0	Audio Interface Setting Register 1	8	0x1B	0x20
18	0	Audio Interface Setting Register 2	8	0x1C	0x00
19	0	Audio Interface Setting Register 3	8	0x1D	0x00
20	0	Clock Setting Register 12 BCLK N Divider	8	0x1E	0x01
21	0	Audio Interface Setting Register 4	8	0x1F	0x00
22	0	Audio Interface Setting Register 5	8	0x20	0x00
23	0	Audio Interface Setting Register 6	8	0x21	0x00
24	0	Digital Interface Misc. Setting Register	8	0x22	0x00
25	0	INT1 Control Register	8	0x30	0x00
26	0	INT2 Control Register	8	0x31	0x00
27	0	GPIO/DOUT Control Register	8	0x34	0x00
28	0	DOUT Function Control Register	8	0x35	0x12
29	0	DIN Function Control Register	8	0x36	0x02

30	0	MISO Function Control Register	8	0x37	0x02
31	0	SCLK/DMDIN2 Function Control Register	8	0x38	0x02
32	0	DAC Instruction Set	8	0x3C	0x01
33	0	DAC Channel Setup Register 1	8	0x3F	0x91
34	0	Page Select Register	8	0x00	0x01
35	1	REF, POR and LDO BGAP Control Register	8	0x01	0x00
36	1	Playback Configuration Register 1	8	0x03	0x00
37	1	Common Mode Control Register	8	0x0A	0x00
38	1	Common Mode Control Register	8	0x0B	0x00
39	1	HP Routing Selection Register	8	0x0C	0x00
40	1	HP Volume Control Register	8	0x16	0x75
41	1	AINL Volume Control Register	8	0x18	0x00
42	1	Output Drivers, AINL, AINR, Control Register	8	0x09	0x00
43	1	HP Driver Gain Setting Register	8	0x10	0x40
44	1	Speaker Volume Control 1	8	0x2E	0x00
45	1	Speaker Amplifier Volume Control 2	8	0x30	0x10
46	1	Speaker Amplifier Control 2	8	0x2D	0x02
47	1	Page Select Register	8	0x00	0x00
48	0	DAC Channel Digital Volume Control Register	8	0x41	0x00
49	0	DAC Channel Setup Register 2	8	0x40	0x04
50	0	Page Select Register	8	0x00	0x2C