



wrong connection, should be connected to SW2

need to add more capacitance according to the output power

need to connect with the external circuit

pin11 should connects with pin26

VCC cap should use 4.7uF

the value of the compensation network depend on the Vin/Vo/Io, Cout

TITLE: EM101U_Daughterboard	
Document Number: EM101U_DB	REV:
Date: 6/3/2020 12:19 AM	Sheet: 1/1